

Product No. RAMO01



MAG ONE BY MOTOROLA BPR40
PORTABLE TWO-WAY RADIO

Product Details

Although care has been taken to ensure the accuracy of the information provided in this Product Specification, CTR is in no way liable for any errors, omissions or changes in specifications.

Features

Group communication

Operates over 8 or 16 channels.

Programmable buttons

Allow versatile customization of radio.

Diecast chassis

Small, lightweight, yet sturdy frame is built to withstand everyday wear and tear.

Flexible power

Offers high-power or low-power option, to save battery charge.

Nuisance channel delete

Temporarily removes undesired channel from a scan.

Repeater talkaround

Bypasses repeater and dispatcher for unit-tounit communication.

Priority channel

Scans for higher-priority channel.

Tight/normal squelch

Filters out unwanted interference and enhances audio clarity.

Product Descriptions

The BPR™40 portable two-way radio delivers reliable, intuitive communication through 8 channels and 2 programmable buttons. The high/low-power option saves battery charge. Features such as nuisance channel delete and repeater talk around make the radio a versatile, high-performance device. The BPR40 is part of the Mag One™ by Motorola radio portfolio. This affordable solution gives remarkable quality and value that is perfect for your business, and comes with a complete assortment of accessories to customize your radio.

Specifications

Estimated battery life 8 hours (high power -

4W/ 5W); 11 hours

(low power - 1W)

Standard battery

chemistry type

Nickel Metal Hydride

Frequency range

VHF:150 - 174 MHz;

UHF: 450 - 470 MHz

1 Watt

Yes

Frequency band

VHF, UHF

Power

1W/4W (UHF), 1W/5W (VHF)

Weight (with

Standard battery)

12.3 oz.

Dimensions

4.21 x 2.28 x 1.46 in.

H x W x D (with standard battery)

Number of channels 8 or 16

Private Line

38

83

Digital Private Line

Cloning

With cable



